

5500W / 6.8KVA INVERTER GENERATOR

5500W / 6.8kva Inverter Generator

Powerbuilt's 6.8KVA pure power open frame inverter generator is suited for emergency household, workshop, or site power. With Powerbuilt's pure power inverter, it's safe to run sensitive electronic equipment, power tools, machinery, and welding equipment. The 32-amp plug is run separately from the 15-amp plugs, ensuring seamless connection to house emergency backup or work sites using lifeguard power distribution systems. The 15-amp plugs are protected by the onboard RCD.

As your emergency power back-up, this unit is ideal for running most single phase worksite equipment, power tools, water pump, charging up devices/lights, most household appliances, fridge, freezer, jug/kettle.

- Heavy-duty open-frame inverter generator with long-range fuel tank
- Push button start with manual recoil start ensures your generator is always ready to go
- 'Eco mode' matches engine RPM to power draw, reduces fuel consumption and noise at low loads
- 11hp, 5500 Watts (6.8kW) Max, 5000 Watts (6.2kW) Rated
- Low oil sensor prevents engine damage from low oil
- 20L Fuel tank with fuel gauge, run time up to 6 hours
- Noise output level 78dB @ 7M away
- 2 x IP66 15amp plugs protected by RCD and individual circuit breakers
- 1 x IP66 32amp plug with circuit breaker for connection to either house or external RCD
- 32amp to 15amp adaptor cable for use with external RCD
- 2 x USB ports

PBI7000X

	MODEL	UNITS	PBI7000X
INVERTER	Max Power	Watts	5500
	Rated Power	Watts	5000
	Max Power	kva	6.87
	Rated Power	kva	6.25
	Amperage	A	21.7
	Hertz	Hz	50
	Voltage	V	230
	Socket		2 x 230V 15amp IP66 1 x 230V 32amp IP66
USB Port		1 x 1 amp 1 x 2.1 amp	
ENGINE	Engine	Hp	11
	Engine Size	cc	292
	RPM	RMP	3600
	Fuel Type		91 Unleaded
	Fuel Tank	L	20
	Run time	Hours	6
	Start Up		Recoil & Electric
Decibel Rating	dba	78dB/7m	
SIZE	Weight (net)	kg	50
	Width	mm	705
	Depth	mm	515
	Height	mm	500



IDEAL FOR RUNNING

Most single phase worksite equipment
Power tools, Water pump
Charging up devices/lights
Most household appliances
Fridge, Freezer, Jug/kettle

