

9500W / 11.8KVA INVERTER GENERATOR

9500W / 11.8kva Inverter Generator

Powerbuilt's 11.8KVA pure power open frame inverter generator is suited for heavy-duty emergency workshop, site or household power. With Powerbuilt's pure power inverter, it's safe to run sensitive electronic equipment, power tools, machinery, and most single-phase welding equipment. The 32-amp plug is run separately from the 15-amp plugs, ensuring seamless connection to house emergency backup or work sites using lifeguard power distribution systems. The 15-amp plugs are protected by the onboard RCD.

As your back-up power source, this unit is ideal for running most single phase worksite equipment, power tools, water pump, air conditioning units, charging up devices/lights, multiple household appliances, fridge, freezer, jug/kettle, and designed to handle large home demands.

- Heavy-duty open-fame inverter generator with long-range fuel tank
- Digital control panel (V.T.F) clearly displays important engine and output data
- Push button start with manual recoil start ensures your generator is always ready to go
- · 'Eco mode' matches engine RPM to power draw, reduces fuel consumption and noise at low loads
- 19hp, 9500 Watts (11.8kW) Max, 9000 Watts (11.25kW) Rated
- Low oil sensor prevents engine damage from low oil
- 38.5L Fuel tank with fuel gauge, run time up to 7 hours
- Noise output level 84dB @ 7M away
- 2x IP66 15amp plugs protected by RCD and individual circuit breakers
- 1x IP66 32amp plug with circuit breaker for connection to
- either house or external RCD
- 32amp to 15amp adaptor cable for use with external RCD
 2x USB ports

PBI12000X

| | MODEL | UNITS | PBI12000X |
|----------|----------------|-------|--|
| INVERTER | Max Power | Watts | 9500 |
| | Rated Power | Watts | 9000 |
| | Max Power | kva | 11.8 |
| | Rated Power | kva | 11.25 |
| | Amperage | A | 39.1 |
| | Hertz | Hz | 50 |
| | Voltage | V | 230 |
| | Socket | | 2 x 230V 15amp IP66 1 x 230V 32amp IP66 |
| | USB Port | | 1 x 1 amp 1 x 2.1 amp |
| ENGINE | Engine | Нр | 19 |
| | Engine Size | сс | 500 |
| | RPM | RMP | 3600 |
| | Fuel Type | | 91 Unleaded |
| | Fuel Tank | L | 38.5 |
| | Run time | Hours | 7 |
| | Start Up | | Recoil & Electric |
| | Decibel Rating | dba | 84dB/7m |
| SIZE | Weight (net) | kg | 80 |
| | Width | mm | 785 |
| | Depth | mm | 615 |
| | Height | mm | 625 |



nush

(M)

IDEAL FOR RUNNING

Most single phase worksite equipment Power tools, Water pump Air conditioning units Charging up devices/lights Multiple household appliances Fridge, Freezer, Jug/kettle Designed to handle large home demands

www.powerbuilttools.co.nz